Hall Tic	Į.	ALLE II	NSTIT				GY & SC		per Code: 18MAT	
M	CA I Year II	Semest	er (R18)	,	UGC-AUT ementary		•	ninations	– September 202	!1
					(Regula	tions: R1	.8)			
T:	- 241		PI	ROBA	BILITY	AND S	TATISTIC	:S		
Time	: 3Hrs	II the au	actions	All nar	ts of the	auaction	must be an	swarad in	Max Marks one place only.	: 60
	Accempe	ii the qu					Part-A or B		one place only.	
Q.1(A)					orem on		•			12M
									e to an overload nce that it is due	
									it both of these	
									problem but no	
	overload									
0.1/0\						OR				
Q.1(B)	given the	note, th	e numb	er of h	oles that	for can b	e drilled pe	r bit. The	density for X is	12M
	given the	x	ig table	2	3	4	5 6	7	8	
		p(x)	0.02	0.03	0.05	_	0.4 0.2	0.07	p(8)	
	(i)	Find P	(8)			JJ		1		
) Find th		for F						
	(ii	i) Use <i>F</i>	to find	the pro	bability t	that a rai	ndomly sele	cted bit c	an be used to	
					nd five h					
		_					e probabiliti	es the sar	ne?	
2 2/4)					bability tl	THE RESERVE TO SHARE THE PARTY OF THE PARTY				
Q.2(A)	V(Y) (iii) co						ifind, (i) $E($	X) and E	(Y) (ii) V(X) and	12M
	v(1) (iii) C		(\Y	0	1	and Y	3	4	1	
		-	0	0						
					0	0	0	1/35		
			1	0	0	0	12/35	0		
			2	0	0	18/35	0	0		
			3	0	4/35	0	0	0		
					(OR	***	-		
(.2(B)	Let X der	note the	tempe	rature ($(^{\circ}C)$ and	let <i>Y</i> de	note the tin	ne in minu	tes that it takes	12M
	for the die	esel eng	ine on	an auto	omobile t	to get re	ady to star	t. Assume	that the joint	
	density for	(X,Y)	is give	n by f	(x,y)=c	(4x+2y)	$+1$); $0 \le x$	$\leq 40, 0 \leq$	<i>y</i> ≤ 2	
	i) Fin	d the va	lue of a	that m	akac thic	2 dancit				

i) Find the value of c that makes this a density

- ii) Find the marginal densities for X and Y.
- iii) Find the probability that on a randomly selected day it will take at least one minute for the car to be ready to start.
- iv) Find the probability that on a randomly selected day the air temperature will exceed $20^{\circ}C$.
- v) Are X and Y independent?

Q.3(A) A computer terminal can pick up an erroneous signal from the keyboard that does not show up on the screen. This creates a silent error that is difficult to detect. Assume that for a particular keyboard the probability that this will occur per entry is 1/1000. In 5000 entries Find the expression fordendity. Also find the probability that (i) No silent error (ii) At least 2 silent errors (iii) At most 3 silent errors occur (iv) write the expression for m.g.f (v) Find mean and variance.

OR

Q.3(B) (i) Derive m.g.f for normal distribution?

12M

12M

- (ii) Among diabetic, the fasting blood glucose level X may be assumed to be approximately normally distributed with mean 106 milligrams and S. D. 8 milligrams.
 - i) Find the probability that randomly selected diabetic will have blood glucose level between 90 and 122 mg.
 - ii) Find $P[X \le 120 \text{mg}]$
 - iii) Find the point that has the property that 25% of all diabetic have a fasting glucose level of this value or lower.
- Q.4(A) (i) Explain the following:

12M

Null and alternative hypotheses (ii) Types of errors (iii) Level of significance (iv) Standard error.

(ii) Random samples of 400 men and 600 women were asked whether they would like to have a flyover near their residence. 200 men and 325 women were in favour of the proposal. Test the hypothesis that the proportions of men and women in favour of the proposal, are same against that they are not, at 5% level.

OR

Q.4(B) A random sample of 10 boys had the following I.Q.: 70, 120, 110, 101, 88, 83, 95, 98, 12M 107, 100. Do these data support the assumption of a population mean I.Q. of 100 (Test at 5% significance level)? Also find 95% confidence interval for population mean I.Q.

12M

Q.5(A) The following table shows the lives in hours of four brands of electric lamps:Brand

A: 1610, 1610, 1650, 1650, 1680, 1700, 1720, 1800

B: 1580, 1640, 1640, 1700, 1750

C: 1460, 1550, 1600, 1620, 1640, 1660, 1740, 1820

D: 1510, 1520, 1530, 1570, 1600, 1680

By shifting the origin to 1640 in the above mentioned data, for simplification in calculation, perform an analysis of variance and test the homogeneity of the mean lives of the four brands of lamps.

OR

Q.5(B) Analyse the following L.S.D. data:

12M

	ı	11	III	IV
Ĩ	12(A)	19(C)	10(B)	8(D)
П	18(C)	12 (B)	6(D)	7(A)
111	22(B)	10(D)	5(A)	21(C)
IV	12(D)	7(A)	27(C)	17(B)

*** END***

Hall Ticket No:											Question Paper Code: 18MCAP103
-----------------	--	--	--	--	--	--	--	--	--	--	--------------------------------

(UGC-AUTONOMOUS)

MCA I Year II Semester (R18) Supplementary End Semester Examinations – September 2021 (Regulations: R18)

	(Regulations: R18)	
	PROGRAMMING IN C	
Time: 3	Wida Ivida Ivida	: 60
A	Attempt all the questions. All parts of the question must be answered in one place only.	
	In Q.no 1 to 5 answer either Part-A or B only	
Q.1(A)	i) What is a variable? What are the rules for declaring variables? Give examples of valid and invalid variables.	8M
	ii) Distinguish between printf() and scanf() in the C language. OR	4M
Q.1(B)	i) Write a C program to swap (exchange) the values of two variables without using temporary variable.	6M
	ii) Explain about different relational operators in C language with example.	6M
Q.2(A)	i) Explain about different types of branching statements in C.	6M
	ii) Write a C program to check whether the given number n is prime or not. OR	6M
Q.2(B)	i) Explain for loop and nested for loop with suitable example.	6M
	ii) Write a c program to find sum of series 1!+2!+3!+4!++n!	6M
Q.3(A)	i) Write a program in C to search for an element using linear search technique.ii) What is an array? How one-dimensional and two-dimensional arrays are declared and initialized. Give suitable example.	6M
	OR	0111
Q.3(B)	i) Define string. Write a c program to find whether the given string is palindrome or not.	6M 6M
	ii) Write a c program to swap two numbers using call by value and call by reference.	• • • • • • • • • • • • • • • • • • • •
Q.4(A)	i) What is a pointer? What are the features of pointers? Write a C program to print address of a variable.	6M
	ii) Write a program to read and display values of an integer array. Allocate space dynamically for the array using the calloc().OR	6M
Q.4(B)	i) Distinguish between array of Structures and an array within structures with an example.	6M 6M
	ii) Differentiate between a structure and union with respective allocation of memory by the compiler. Given an example of each.	
2.5(A)	A file name data.txt contains a series of integers, write a program to read these numbers, write all odd numbers to a file odd.txt and even numbers to a even.txt OR	12N
Q.5(B)	Explain different types of file handling function in c programming language.	12N
	*** END***	

Hall Ticket No:								Question Paper Code: 18MCAP104
-----------------	--	--	--	--	--	--	--	--------------------------------

(UGC-AUTONOMOUS)

MCA I Year II Semester (R18) Supplementary End Semester Examinations – September 2021 (Regulations: R18)

DATABASE MANAGEMENT SYSTEMS

Time:	Time: 3Hrs Max Marks: 60							
	Attempt all the questions. All parts of the question must be answered in one place only. In Q.no 1 to 5 answer either Part-A or B only							
Q.1(A)	Explain the functions of DBA.	12M						
	OR							
Q.1(B)	Explain the overall system architecture of DBMS.	12M						
Q.2(A)	Explain nested queries with examples.	12M						
	OR							
Q.2(B)	Write notes on the following. (i) DDL (ii) DML	12M						
Q.3(A)	What is mutivalued dependency? Explain 4NF.	12M						
	OR							
Q.3(B)	Explain BCNF with an example.	12M						
Q.4(A)	Explain about Lock based concurrency control mechanism.	12M						
	OR							
Q.4(B)	Explain about Aries recovery algorithm.	12M						
Q.5(A)	Explain the aggregate functions in SQL with example	12M						
	OR							
Q.5(B)	(i) What is a Trigger? (ii) Explain about triggers in PL/SQL with example. *** END***	12M						

Hall Ticket No:						Question Paper Code: 18MCAP105

(UGC-AUTONOMOUS)

MCA I Year II Semester (R18) Supplementary End Semester Examinations – September 2021 (Regulations: R18)

OPERATING SYSTEMS								
Tin	ne: 3Hrs Max Marks: 6	0						
	Attempt all the questions. All parts of the question must be answered in one place only. In Q.no 1 to 5 answer either Part-A or B only							
Q.1(A)	Why the system calls are to be provided by Operating System? What system calls are provided by a typical OS? Explain in detail. OR	12M						
Q.1(B)	What is operating system? Explain the functions and objectives of operating system.	12M						
Q.2(A)	Define AWK. Illustrate the fields and records in AWK.	12M						
	OR							
Q.2(B)	Compare and contrast the Process utilities and Disk utilities.	12M						
Q.3(A)	Write a short note on the following; i) arithmetic in shell ii) debugging shell scripts	12M						
	OR							
Q.3(B)	List and explain the shell responsibilities.	12M						
Q.4(A)	What is scheduling? Why is it necessary? Describe the various process scheduling algorithms available.	12M						
	OR							
Q.4(B)	Consider a system with three processes and four resources. Resource R1 and R3 with one instance, R2 with two instance, process P1 holding an instance of R2 and waiting for r1,process P2 is holding an instance of R1 and R2 and waiting for R3,process P3 is holding an instance of R3. i) Draw resource allocation graph to the given system. ii) Is it possible to apply the Resource allocation graph algorithm to avoid deadlock? Explain	12M						
O E/A)	What is mounting of a file system? How mounting takes place in different operating	12M						
Q.5(A)	austana). Evalain with avamala							
Q.5(A)	system? Explain with example. OR							
Q.5(B)		12M						

Page 1 of 1

Hall Ticket No: Question Paper Code: 1
--

(UGC-AUTONOMOUS)

MCA I Year II Semester (R18) Supplementary End Semester Examinations – September 2021 SOFTWARE ENGINEERING

	SOFTWARE ENGINEERING	
Time:	: 3Hrs Max	Marks: 60
	Attempt all the questions. All parts of the question must be answered in one place only In Q.no 1 to 5 answer either Part-A or B only	•
Q.1(A)	Describe "Software myth". Discuss on various types of software myths and the true aspects of these myths.	e 12
	OR	
Q.1(B)	Explain Software Engineering. Explain the Software Engineering Layers.	12M
Q.2(A)	Construct the scenario based elements with a use case – "Online Shopping Cart"	12M
	OR	
Q.2(B)	Write about flow based modeling in detail with an example	12M
Q.3(A)	i. Write about architectural styles and patterns. (6M) ii. Explain how map data flow into software architecture.(6M) OR	12M
Q.3(B)	Explain architectural context diagram for the Safe Home Security function.	12M
Q.4(A)	Write about user interface analysis and design in detail.	12M
	OR	
Q.4(B)	i. Illustrate Aesthetic design. ii. Explain about content design and Architecture design in detail.	12M
Q.5(A)	 i. Discuss the importance of the test strategies for conventional software.(6M) ii. Describe Various functional and unit testing techniques in detail(6M) OR 	12M
Q.5(B)	Explain a simple notation for the representation of control flow.	12M
	*** END***	